




E57USA Electric Siren





- Omni directional outdoor warning
- 105 decibel signal for public warning or fire-volunteers call
- Penetrating signal of 490 Hertz
- Easy installation on roof
- Pole mount optional
- 240V, three phase 5 KW motor
- Mushroom shape, environmental friendly
- Based on original siren used in WWII and still more than 6,000 units in service
- Easy replacement of old Fire House sirens
- Various controls available (purchased separately)


Sound Pressure Level	105 dB (c)
Power Requirement	240 Volt AC, Three Phase, 22 Amps
Motor	Asynchronous with Squirrel Cage Rotor
Weight	142 Pounds
Mounting Method	Flat plate (included) or pole mounting (optional)



- 

The E57USA Electromechanical Siren is the perfect solution for Fire Departments that use sirens mounted on Fire Stations for recalling department personnel and notifying the community of fires or other emergencies. Various plants that need to warn their employees during emergencies can use the siren with local or remote activation.
- 

It also serves as a low cost component for large scale emergency notification systems such as those used for severe weather warnings.
- 

Can sound various signal patterns, based on the controller.
- 

The E57USA is rugged, reliable, and can be activated by a local mechanical switch or by radio or fixed wire via relay. Signal controls of currently installed old siren can operate this siren when using auto-starter (optional), and can sound the same signal pattern as used today.

837 Arnold Drive, Suite 600, Martinez, California 94553-6534 USA

Telephone (925) 228-2152 · Fax (925) 228-2114 ·